


今まで無かったエンドミルチャック



■ 7/24テーパ



(Unit: mm)

Model NO.	D	L1	L	G
BT40-ERA11-70	22	45	70	M18x1P
BT40-ERA11-100	22	75	100	M18x1P
BT40-ERA16-70	28	45	70	M24x1P
BT40-ERA16-100	28	75	100	M24x1P
BT40-ERA20-80	32	55	80	M28x1.5P
BT40-ERA20-100	32	75	100	M28x1.5P
BT40-ERA25-80	38	55	80	M32x1.5P
BT40-ERA25-100	38	75	100	M32x1.5P
BT40-ERA32-80	46	45	80	M40x1.5P
BT40-ERA32-100	46	75	100	M40x1.5P
BT50-ERA11-80	22	45	80	M18x1P
BT50-ERA11-110	22	75	110	M18x1P
BT50-ERA16-80	28	55	80	M24x1P
BT50-ERA16-110	28	75	110	M24x1P
BT50-ERA20-90	32	55	90	M28x1.5P
BT50-ERA20-110	32	75	110	M28x1.5P
BT50-ERA25-90	38	55	90	M32x1.5P
BT50-ERA25-110	38	75	110	M32x1.5P
BT50-ERA32-90	46	55	90	M40x1.5P
BT50-ERA32-110	46	75	110	M40x1.5P

精度 コスト 永続性
総てに定評の高い
世界中に流通する
ERコレットを採用

高速回転に全品デー
ター添付で保証します

最小外径は22φで7φ
迄のエンドミルが
掴めます。

これだけ高性能で
驚く価格で供給します

BT30で爪無しも製作
可能、30000rpmでも
スムーズです。


ER8, ER11, ER16, ER20, ER25, ER32, ER40

EUROで標準規格



まずコレットとナットを取り付けてから
本体装着下さい。

■ 寸法関係



(Unit: mm)

Model No.	D1	H	D2
ER11	11.5	18	1, 1.5, 2, 2.5, 3, 3.5, 4, 4.5, 5, 5.5, 6, 6.5, 7
ER16	17	27	1, 2, 3, 4, 5, 6, 7, 8, 9, 10
ER20	21	31	2, 3, 4, 5, 6, 7, 8, 9, 10, 11, 12, 13
ER25	26	35	2, 3, 4, 5, 6, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16
ER32	33	40	3, 5, 6, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20
ER40	41	46	4, 5, 6, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 21, 22, 23, 24, 25, 26

Model No.	D1	H	D2
ER11	11.5	18	1/32, 1/16, 3/32, 1/8, 3/16, 7/32, 1/4
ER16	17	27	1/32, 1/16, 3/32, 1/8, 3/16, 7/32, 1/4, 5/16, 11/32, 3/8
ER20	21	31	1/16, 3/32, 1/8, 3/16, 7/32, 1/4, 5/16, 11/32, 3/8, 13/32, 7/16, 1/2
ER25	26	35	1/16, 3/32, 1/8, 3/16, 7/32, 1/4, 5/16, 11/32, 3/8, 13/32, 7/16, 1/2, 17/32, 9/16, 5/8
ER32	33	40	3/32, 1/8, 3/16, 7/32, 1/4, 5/16, 11/32, 3/8, 13/32, 7/16, 1/2, 17/32, 9/16, 5/8, 21/32, 11/16, 3/4, 25/32
ER40	41	46	1/8, 3/16, 7/32, 1/4, 5/16, 11/32, 3/8, 13/32, 7/16, 1/2, 17/32, 9/16, 5/8, 21/32, 11/16, 3/4, 25/32, 13/16, 27/32, 7/8, 15/16, 31/32, 1